



# Moticam BTI10 Plus

<b>SAP Code</b>	1100600101511
<b>Sensor</b>	1/3" CMOS Sensor
<b>Imaging area</b>	5.44 x 3.07mm
<b>Capture resolution</b>	4MP
<b>Pixel size (um)</b>	2.0 x 2.0µm
<b>Scan mode</b>	Progressive
<b>Shutter mode</b>	Rolling Shutter
<b>Operating Temperature</b>	-10 ~ +50°C
<b>Operating Humidity</b>	30~80%RH
<b>Lens mount</b>	C-Mount
<b>Software</b>	MotiConnect for Android/iOS/Windows/Mac OS
<b>Package Includes</b>	10" tablet, 12V Power Adapter, USB cable, CS Ring, Motic 4-dot calibration slide, Dust Cap, Manual

## INTERFACE & BUTTON FUNCTIONS

<b>USB</b>	USB 5V Output
<b>RJ45</b>	LAN Port, Default IP: 192.168.2.151
<b>WiFi</b>	2.4G/5G (Suport 802.11ac), Default IP:192.168.1.151
<b>DC12V</b>	DC12V/2.5A
<b>LED</b>	Orange LED, Blue LED
<b>RST</b>	Reset, 10s

## VIDEO

<b>Image Compression Engine</b>	H264 or MJPEG
<b>Major Stream</b>	1920x1080,1280x720
<b>Minor Stream</b>	640x360
<b>MJPG</b>	1280x720
<b>Still(Capture)</b>	2560x1440
<b>Frame rate</b>	30fps



\*Frames per second under optimal lighting conditions and in compliance with computer technical requirements.